

# Recover<sup>me</sup>

AZBox Me | AZBox miniMe



If a problem occurs during a firmware flash or update and you need to recover your AZbox Me/miniMe, please follow the steps below.

- 1 Turn ME off with the on/off switch (on the rear panel);
- 2 Shift the switch, on the rear panel, from “normal” to “recovery”;
- 3 Turn ME on with the on/off switch, and then push the power button (on the front panel);
- 4 Wait until the display shows “Done”;
- 5 Turn ME off with the on/off switch;
- 6 Shift the switch from “recovery” to “normal”;
- 7 Connect ME to the Internet through the LAN connection;
- 8 Turn ME on with the on/off switch, and then push the power button;
- 9 Wait until the display shows the IP address of the box;
- 10 Type the IP address on your Web Browser;
- 11 Select “firmware upgrade (BOOT 0)”;
- 12 Then press “choose file”, and get the most recent firmware (*download from [www.azbox.com](http://www.azbox.com) at the Downloads tab*);
- 13 Once you have chosen, just press “upload”;
- 14 When it's done, you will need to select “reboot” and press “flash”;
- 15 The box will update and restart.

Edifício AZBox, Lagoa S/N  
4950-283 Mazedo, MNÇ | PORTUGAL  
Tel: +351 251 656 134 / Fax: +351 251 652 966  
[info@azbox.com](mailto:info@azbox.com) | [www.AZBox.com](http://www.AZBox.com)